

## **Quarterly Reliability Monitoring Results**

## Quarters: Q3/2021 to Q4/2022

Based on structural similarity

Supplier Nexperia B.V. Name of Laboratory		User Part Number						
		PCMF2HDMI2S						
		Part Description						
		NXP ICN8	Protection IND	OI				
Assembly reliability labs		WLCSP package						
Test		Test Conditions	Duration	# Lots	# Quantity	# Rejects		
	TEST							
	Pre- and Post-Stress							
# 1	Electrical Test	Tamb = 25 °C	N/A	see below	all parts	see below		
		MIL-STD-750-1						
	HTRB	M1038 Method A						
		Tj = Tjmax, Vr = 100% of max. datasheet						
# 5	Bias	reverse voltage	1000 hours	68	4040	0		
	тс	JESD22-A104						
# 7	Temperature Cycling	-40 °C to 125°C	1000 cycles	24	1440	0		
	UHAST	JESD22-A118						
# 8 <b>or</b>	Unbiased HAST	Tamb = 130 °C, RH = 85 %						
	Olibiased HAST		- 96 hours	n.a.	n.a.	n.a.		
	••	JESD22-A102						
	AC Autoclave	Tamb = 121 °C, RH = 100 %						
# 8a	Autociave	Pressure = 205 kPa (29.7 psia)						
	HAST	JESD22-A110						
	Highly Accelerated Stress	Tamb = 130 °C, RH = 85%, VR = 80 % of						
# 9	Test	rated reverse voltage <sup>[1]</sup>	1000 hours	24	1440	0		
# 3		MIL-STD-750 Method 1037	1000 110013	24	1440	0		
	IOL	ton = toff, devices powered to insure $\Delta T_j$ =						
# 10	Intermittent Operating Life		1000 hours					
# 10	Intermittent Operating Life	100 C 101 15000 Cycles	1000 110015	n.a.	n.a.	n.a.		
	RSH	JESD22-A111						
# 20	Resistance to Solder Heat	260 °C ± 5 °C	10 s	n.a.	n.a.	n.a.		
	SD							
# 21	Solderability	J-STD-002		n.a.	n.a.	n.a.		

<sup>[1]</sup>The maximum applied voltage is limited by test chamber set up and does not exceed 115V.

## **Calculation of FIT and MTTF**

Test considered for FIT calculation: High Temperature Reverse Bias (HTRB, Test # 5) Confidence level 60%, derated to 55 °C, activation energy 0.7 eV, test time 168 to 1000 hours

Wafer Fab	Technology	Quantity	Rejects	Failure Rate (FIT)	MTTF (hrs)
NXP ICN8	Protection INDI	4040	0	1,1	9,51E+08

<sup>© 2023</sup> Nexperia B.V.

All information hereunder is per Nexperia's best knowledge. This document does not provide for any representation or warranty express or implied by Nexperia. In case Nexperia has tested the product, this documentation reflects the outcome of the analysis of the actually tested parts only.

nexperia.com