

## **Quarterly Reliability Monitoring Results**

## Quarters: Q1/2021 to Q4/2021

Based on structural similarity

<b>Supplier</b> Nexperia B.V.		User Part Number						
		PDTC143EQB						
Name of Laboratory  Assembly reliability labs		Part Description						
		Nexperia DHAM Small Signal Bipolar Transistor						
		MCD package						
Test		Test Conditions	Duration	# Lots	# Quantity	# Rejects		
	<b>TEST</b> Pre- and Post-Stress							
# 1	Electrical Test	Tamb = 25 °C	N/A	see below	all parts	see below		
# 2	<b>PC</b> Preconditioning	JESD22-A113 Bake Tamb = 125 °C Soak Tamb = 85 °C, RH = 85% Reflow soldering	24 hours 168 hours 3 cycles	208	16640	0		
# 5	HTRB High Temperature Reverse Bias	MIL-STD-750-1 M1039 Method A Tj = Tjmax, Vr = 100% of max. datasheet reverse voltage	1000 hours	202	16160	0		
# 7	<b>TC</b> Temperature Cycling	JESD22-A104 -65 °C to Tjmax, not to exceed 150°C	500 cycles	52	4160	0		
# 8	<b>AC</b> Autoclave	JESD22-A102 Tamb = 121 °C, RH = 100 % Pressure = 205 kPa (29.7 psia)	96 hours	52	4160	0		
# 9	<b>H3TRB</b> High Humidity High Temperature Reverse Bias	JESD22-A101 Tamb = 85 °C, RH = 85%, VR = 80 % of rated reverse voltage $^{[1]}$	1000 hours	52	4160	0		
# 10	<b>IOL</b> Intermittent Operating Life	MIL-STD-750 Method 1037 ton = toff, devices powered to insure $\Delta Tj$ = 100 °C for 15000 cycles	1000 hours	52	4160	0		
# 20	<b>RSH</b> Resistance to Solder Heat	JESD22-A111 260 °C ± 5 °C	10 s	n.a.	n.a.	n.a.		
# 21	<b>SD</b> Solderability	J-STD-002		111	1110	0		

<sup>[1]</sup> The maximum applied voltage is limited by test chamber set up and does not exceed 115V.

## **Calculation of FIT and MTTF**

Test considered for FIT calculation: High Temperature Reverse Bias (HTRB, Test # 5) Confidence level 60%, derated to 55 °C, activation energy 0.7 eV, test time 168 to 1000 hours

Wafer Fab	Technology	Quantity	Rejects	Failure Rate (FIT)	MTTF (hrs)
Nexperia	Small Signal Bipolar				
DHAM	Transistor	16160	0	0.26	3.81E+09

© 2022 Nexperia B.V.

All information hereunder is per Nexperia's best knowledge. This document does not provide for any representation or warranty express or implied by Nexperia. In case Nexperia has tested the product, this documentation reflects the outcome of the analysis of the actually tested parts only.

nexperia.com